



Model: WS for SCHNEIDER MTN515125 LOW V

Family: WALL-SMART

DWG NO. 10-04-572-SPC



Model No.: 10-01-572

PRODUCT SPEC.

REVISION A

DATE 20/Mar./2016

Make Your Wall Smart

“WS for SCHNEIDER MTN515125 LOW V” - Product description:

The “WS for SCHNEIDER MTN515125 LOW V” is an adapter for in-wall flush installation of a MTN515125 M-Plan frame and low voltage keypad. The “WS for SCHNEIDER MTN515125 LOW V” securely mounts the M-Plan frame and the low voltage keypad while allowing easy access, insertion and removal.

Key features and benefits:

- Flush with the wall.
- Paintable with the wall paint in any color and texture.
- Allows easy insertion and removal of the keypad by manual push and magnet detachment.
- The adapter is supplied unpainted (To be painted after installation as part of the wall).
- Designed to be installed in ½” drywall. Installation of the Wall-Smart adapter is straight-forward. Installation process is similar to drywall construction procedures. Before installation, read Wall-Smart installation instruction 10-04-00101-INS in <http://www.wall-smart.com/faq>
- For installation in concrete/block wall use “WS Concrete Box 152x152” P/N 10-01-077 (sold separately) according installation instruction 10-04-00103-INS in <http://www.wall-smart.com/faq>
- Designed for the use with MTN515125 M-Plan frame and the low voltage keypad (by Schneider) (frame and keypad are not included).
- Adapter kit contains:
 1. Wall adapter;
 2. Keypad adapter;
 3. (X4) M3x12 screws
 4. (X4) M3 nuts

Key properties:

- Dimensions (W/H/D): 152mm (5.98")/ 152mm (5.98")/ 22mm (0.87")
- Weight: 0.2Kg, 0.44pounds.
- Material: Moisture resistant MDF
- To be installed in ½” drywall (for installation in 5/8” drywall use 1/8” shim pack P/N 10-01-067 (sold separately)).

