



Model: WS NC FOR LUTRON PICO

Model No.: 058-1-376

Family: WALL-SMART

DWG NO. 058-4-376-SPC

PRODUCT SPEC.

REVISION A

DATE 16/JAN/2022



Make Your Wall Smart

“WS NC FOR LUTRON PICO” - Product description:

The “WS NC FOR LUTRON PICO” is an adapter for in-wall flush installation of LUTRON Pico keypad.

The “WS NC FOR LUTRON PICO” firmly mounts the keypad while allowing easy access, insertion and operation.

Key features and benefits:

- Flush with the wall.
- Paintable with the wall paint in any color and texture.
- Allows easy insertion and removal of the device.
- The adapter is supplied unpainted (To be painted after installation as part of the wall).
- Designed to be installed in 1/2” drywall. Installation of the Wall-Smart adapter is straight-forward. Installation process is similar to drywall construction procedures. Before installation, read Wall-Smart installation instruction 10-04-00101-INS in <http://www.wall-smart.com/faq>
- Designed for the use with LUTRON Pico keypad (not included).
- Adapter kit contains:
 1. Wall adapter (x1)
 2. Keypad adapter (x1)
 3. CS M3x10 Screws (x2)
 4. M3 Nuts (x2)

Key properties:

- Dimensions (W/H/D): 105mm (4.13")/ 139mm (5.47")/ 16.6mm (0.65")
- Power Supply: None (manual adapter).
- Weight: 0.15Kg, 0.33lbs.
- Material: Moisture resistant MDF
- To be installed in 1/2” drywall (for installation in 5/8” drywall use 1/8” shim pack P/N 10-01-067 (sold separately)).

