



Model: WS for C4 Decora Wired Keypad

Family: WALL-SMART

DWG NO. 10-04-058-SPC

Model No.: 10-01-058

PRODUCT SPEC.

REVISION A

DATE 28/Oct./2014



Make Your Wall Smart

“WS for C4 Decora Wired Keypad” - Product description:

The “WS for C4 Decora Wired Keypad” is an adapter for in-wall flush installation of a Control4 “Decora” style keypad.

The “WS for C4 Decora Wired Keypad” securely mounts the keypad while allowing easy access, insertion and removal.

Key features and benefits:

- Flush with the wall.
- Paintable with the wall paint in any color and texture.
- Allows easy insertion and removal of the keypad by manual push and magnet detachment of the keypad tray.
- The adapter is supplied unpainted (To be painted after installation as part of the wall).
- Designed to be installed in ½” drywall. Installation of the Wall-Smart adapter is straight-forward. Installation process is similar to drywall construction procedures. Before installation, read Wall-Smart installation instruction 10-04-00101-INS in <http://www.wall-smart.com/faq>
- For installation in concrete/block wall use “WS CONCRETE ADAPTOR FOR C4 Decora Keypad” P/N 10-01-253 (sold separately) according installation instruction 10-04-00103-INS in <http://www.wall-smart.com/faq>
- Designed for the use with Control4 “Decora” style keypad. (keypad not included).
- Adapter kit contains:

- Wall adapter (item 2)
- Keypad bezel (item 1)
- (4x) ST3.5 Screws (item 3)

Key properties:

- Dimensions (W/H/D): 138mm (5.4")/ 180mm (7.1")/ 16.6mm (0.65")
- Power Supply: None (manual adapter).
- Weight: 0.237Kg, 0.52lbs.

