



Model: WS FOR BERKER B.IQ push-button
4G Stainless steel

Family: WALL-SMART

DWG NO. 10-04-568-SPC



Model No.: 10-01-568

PRODUCT SPEC.

REVISION A

DATE 20/Mar./2016

Make Your Wall Smart

“WS FOR BERKER B.IQ push-button 4G Stainless steel”

- Product description:

The “WS FOR BERKER B.IQ push-button 4G Stainless steel” is an adapter for in-wall flush installation of a B.IQ 4G Stainless steel keypad. The “WS FOR BERKER B.IQ push-button 4G Stainless steel” securely mounts the keypad while allowing easy access, insertion and removal.

Key features and benefits:

- Flush with the wall.
- Paintable with the wall paint in any color and texture.
- Allows easy insertion and removal of the keypad by manual push and magnet detachment.
- The adapter is supplied unpainted (To be painted after installation as part of the wall).
- Designed to be installed in ½” drywall. Installation of the Wall-Smart adapter is straight-forward. Installation process is similar to drywall construction procedures. Before installation, read Wall-Smart installation instruction 10-04-00101-INS in <http://www.wall-smart.com/faq>
- For installation in concrete/block wall use “WS Concrete Box 200x160” P/N 10-01-181 (sold separately) according installation instruction 10-04-00103-INS in <http://www.wall-smart.com/faq>
- Designed for the use with B.IQ 4G Stainless steel keypad (by BERKER) (keypad is not included).
- Adapter kit contains:
 1. Wall adapter;
 2. Keypad adapter;
 3. (X6) M3x12 screws
 4. (X6) M3 nuts

Key properties:

- Dimensions (W/H/D): 159.4mm (6.28")/ 198.8mm (7.83")/ 25.9mm (1.02")
- Weight: 0.3Kg, 0.66Lbs.
- Material: Moisture resistant MDF
- To be installed in ½” drywall (for installation in 5/8” drywall use 1/8” shim pack P/N 10-01-067 (sold separately)).

