



Model: WS for BERKER B.IQ 3G
Polar white matte

Family: WALL-SMART

DWG NO. 10-04-660-SPC



Model No.: 10-01-660

PRODUCT SPEC.

REVISION A

DATE 20/Mar./2016

Make Your Wall Smart

“WS for BERKER B.IQ 3G Polar white matte”

- Product description:

The “WS for BERKER B.IQ 3G Polar white matte” is an adapter for in-wall flush installation of a B.IQ 3G Polar white matte push-button.

The “WS for BERKER B.IQ 3G Polar white matte” securely mounts the push-button while allowing easy access, insertion and removal.

Key features and benefits:

- Flush with the wall.
- Paintable with the wall paint in any color and texture.
- Allows easy insertion and removal of the push-button by manual push and magnet detachment.
- The adapter is supplied unpainted (To be painted after installation as part of the wall).
- Designed to be installed in 1/2” drywall. Installation of the Wall-Smart adapter is straight-forward. Installation process is similar to drywall construction procedures. Before installation, read Wall-Smart installation instruction 10-04-00101-INS in <http://www.wall-smart.com/faq>
- For installation in concrete/block wall use “WS Concrete Box 165X165” P/N 10-01-521 (sold separately) according installation instruction 10-04-00103-INS in <http://www.wall-smart.com/faq>
- Designed for the use with B.IQ 3G Polar white matte push-button (by BERKER) (push-button is not included).
- Adapter kit contains:

1. Wall adapter;
2. Keypad adapter;
3. (X4) M3x12 screws
4. (X4) M3 nuts

Key properties:

- Dimensions (W/H/D): 164mm (6.46")/ 164mm (6.46")/ 26.2mm (1.03")
- Weight: 0.26Kg, 0.57Lbs.
- Material: Moisture resistant MDF
- To be installed in 1/2” drywall (for installation in 5/8” drywall use 1/8” shim pack P/N 10-01-067 (sold separately)).

