



Model: WS for BERKER B.IQ 3G Polar white matte W.Thermostat

Family: WALL-SMART

DWG NO. 10-04-661-SPC



Model No.: 10-01-661

PRODUCT SPEC.

REVISION A

DATE 20/Mar./2016

Make Your Wall Smart

“WS for BERKER B.IQ 3G Polar white matte W.Thermostat”

- Product description:

The “WS for BERKER B.IQ 3G Polar white matte W.Thermostat” is an adapter for in-wall flush installation of a B.IQ 3G Polar white matte with thermostat keypad.

The “WS for BERKER B.IQ 3G Polar white matte W.Thermostat” securely mounts the keypad while allowing easy access, insertion and removal.

Key features and benefits:

- Flush with the wall.
- Paintable with the wall paint in any color and texture.
- Allows easy insertion and removal of the keypad by manual push and magnet detachment.
- The adapter is supplied unpainted (To be painted after installation as part of the wall).
- Designed to be installed in ½” drywall. Installation of the Wall-Smart adapter is straight-forward. Installation process is similar to drywall construction procedures. Before installation, read Wall-Smart installation instruction 10-04-00101-INS in <http://www.wall-smart.com/faq>
- For installation in concrete/block wall use “WS Concrete Box 200x160” P/N 10-01-181 (sold separately) according installation instruction 10-04-00103-INS in <http://www.wall-smart.com/faq>
- Designed for the use with B.IQ 3G Polar white matte with thermostat keypad (by BERKER) (keypad is not included).
- Adapter kit contains:
 1. Wall adapter;
 2. Keypad adapter;
 3. (X6) M3x12 screws
 4. (X6) M3 nuts

Key properties:

- Dimensions (W/H/D): 159.4mm (6.28")/ 198.8mm (7.83")/ 26.9mm (1.06")
- Weight: 0.3Kg, 0.66Lbs.
- Material: Moisture resistant MDF
- To be installed in ½” drywall (for installation in 5/8” drywall use 1/8” shim pack P/N 10-01-067 (sold separately)).

